

*The finest name in paging is back and our promise is simple.*



Provide the highest quality product, the fastest delivery, and accurate fulfillment, at competitive prices.



# BR-802

## New Features

- Programmable Group Name (PPS)
- Programmable Personal Folders Name (PPS)
- Programmable memory allocation (PPS)
- Programmable Maildrop Folder Name (PPS)
- Programmable Notebook Folder Name (PPS)
- Show Source ID
- Change Battery w/out turning off pager.
- No Screen Blank when message received.

## PERFORMANCE SPECIFICATIONS

900 Mhz FLEX	
<b>Model Number:</b>	Br802
<b>Frequency</b>	929 - 932 MHz 135-175
<b>Code Format</b>	FLEX, 1600/3200/6400 bps
<b>Channel Spacing</b>	25 kHz
<b>Frequency deviation</b>	+/- 4.8 kHz
<b>Paging Sensitivity</b>	10 mV/m for 6400 bps,
<b>EIA Selectivity</b>	55 dB
<b>EIA Spurious and Image</b>	50 dB
<b>IM Rejection</b>	50 dB
<b>Operating Temp</b>	-10°C to 50°C
<b>Alert Tone Loudness</b>	75 dB @ 12 inches
<b>Battery Type</b>	1 x Alkaline AA
<b>Battery Life</b>	~ 100 days (collapse value =4)
<b>Weight (with battery)</b>	60 grams
<b>Size</b>	80 x 55 x 18mm

